



### **HX 3000 TB UK C5**

PORTABLE POWER

**GENERATING SET Range INTENS** 

#### **PRODUCT ADVANTAGES**

- · Solid and high-performance equipment
- Generating set guaranteed 3 years
- **HONDA Professional Engine**

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

#### Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



















This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

## **HX 3000 TB UK C5**

#### **GENERAL SPECIFICATIONS**

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	2.70
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	3.10
75% cons. (I/h) *	1.30
75% Autonomy (h) *	2.40
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	67

#### **ENGINE SPECIFICATIONS**

Engine brand	HONDA
Engine type	GX200_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	196
Oil system capacity including filters (I)	0.60

#### ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	Н

#### PLUGS AND PANEL DESCRIPTIVE

2 115V 16A sockets - circuit breaker + 1 socket 230V 16A - circuit breaker

#### **DIMENSIONS AND WEIGHT**

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kg)	41

#### **PACKAGING**

Packaging type	Box
Length (cm)	60.50
Width (cm)	46
Height (cm)	44
Weight (kg)	43
Pallet type	140/110
Number of box by pallet	15
Pallet height (cm)	145
weight of the packaged Pallet (kg)	661





# **HX 3000 TB UK C5**

#### **ACCESSORIES SUPPLIED**



Funnel



User and maintenance manual

### **OPTIONS**



R05M - Manual source inverter for connecting a single-phase generator to a house

Manual source inverter for connecting a single-phase generator to a house



R06 - Trolley kit for HX 3000 / HXC 3000 ; Puncture-proof wheels Ø 187 mm

Trolley kit for HX 3000 / HXC 3000 ; Puncture-proof wheels Ø 187 mm



R18 - Maintenance kit for HX 3000 including oil, spark plug and air filter

Maintenance kit for HX 3000 including oil, spark plug and air filter



16A blue 230V male plug -Sold per 1 or 10

16A blue 230V male plug - Sold per 1 or 10



16A yellow 115V male plug -Sold per 1 or 10

16A yellow 115V male plug - Sold per 1 or 10



Adaptator R54 16A/13A adaptator unit. Sold per 1 or

Adaptator R54 16A/13A adaptator unit. Sold per 1 or 3



ADAPTATOR R55 16A/13A adaptator economy. Sold per 1 or 3

ADAPTATOR R55 16A/13A adaptator economy. Sold per 1 or 3



ADAPTATOR R56 16A/13A double adaptator. Sold per 1 or 3

ADAPTATOR R56 16A/13A double adaptator. Sold per 1 or 3



RBH1 - Box of 20 cans of 1L oil (15W40) for INVERTER / PERFORM / PERFORM XL / HX / TECHNIC 6500 - 7500 / DIESEL 4000 / WELDARC 200 / VX 200/4 / AQUALINE

Box of 20 cans of 1L oil (15W40) for INVERTER / PERFORM / PERFORM XL / HX / TECHNIC 6500 - 7500 / DIESEL 4000 / WELDARC 200 / VX 200/4 / AQUALINE



RBHO-5 - Box of 24 cans of 0.5L oil (15W40) for INVERTER / PERFORM / PERFORM XL / HX / TECHNIC 6500 - 7500 /

Box of 24 cans of 0.5L oil (15W40) for INVERTER / PERFORM / PERFORM XL / HX / TECHNIC 6500 - 7500 / DIESEL 4000 / WELDARC 200 / VX 200/4 / AQUALINE



5/19/2024



**DIESEL 4000 / WELDARC** 200 / VX 200/4 / AQUALINE **RHO - Protective cover for** HX 3000 / HXC 3000 /

PRESTIGE 3000 / ST 2,36 - 3,60 / TR 2,36 - 3,60 / HP 2,26 / XT 3,78 ; Dimensions : 70 x 45 x 50 cm

PERFORM 3000 - 3000 XL / Protective cover for HX(C) 3000 / PERFORM 3000 - 3000 XL / PRESTIGE 3000 / ST 2,36 - 3,60 / TR 2,36 - 3,60 / HP 2,26 / XT 3,78 ; Dimensions : 70 x 45 x 50 cm