



HX 3000 C5 RCD

PORTABLE POWER

GENERATING SET Range INTENS

PRODUCT ADVANTAGES

- Inclusive differential protection
- Generating set guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

HX 3000 C5 RCD

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	2.70
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	3.10
75% cons. (l/h) *	1.30
75% Autonomy (h) *	2.40
Sound power level guaranteed LwA dB(A)	95
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	67

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX200_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	196
Oil system capacity including filters (l)	0.60

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker + Residual Current Device

DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kg)	41

PACKAGING

Packaging type	Box
Length (cm)	60.50
Width (cm)	46
Height (cm)	44
Weight (kg)	43
Pallet type	140/110
Number of box by pallet	15
Pallet height (cm)	145
weight of the packaged Pallet (kg)	661



5/18/2024

HX 3000 C5 RCD - PORTABLE POWER - GENERATING SET INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

OPTIONS



R05M - Manual source inverter for connecting a single-phase generator to a house

Manual source inverter for connecting a single-phase generator to a house



R06 - Trolley kit for HX 3000 / HXC 3000 ; Puncture-proof wheels Ø 187 mm

Trolley kit for HX 3000 / HXC 3000 ; Puncture-proof wheels Ø 187 mm



R18 - Maintenance kit for HX 3000 including oil, spark plug and air filter

Maintenance kit for HX 3000 including oil, spark plug and air filter



RBH1 - Box of 20 cans of 1L oil (15W40) for INVERTER / PERFORM / PERFORM XL / HX / TECHNIC 6500 - 7500 / DIESEL 4000 / WELDARC 200 / VX 200/4 / AQUALINE

Box of 20 cans of 1L oil (15W40) for INVERTER / PERFORM / PERFORM XL / HX / TECHNIC 6500 - 7500 / DIESEL 4000 / WELDARC 200 / VX 200/4 / AQUALINE



RBHO-5 - Box of 24 cans of 0.5L oil (15W40) for INVERTER / PERFORM / PERFORM XL / HX / TECHNIC 6500 - 7500 / DIESEL 4000 / WELDARC 200 / VX 200/4 / AQUALINE

Box of 24 cans of 0.5L oil (15W40) for INVERTER / PERFORM / PERFORM XL / HX / TECHNIC 6500 - 7500 / DIESEL 4000 / WELDARC 200 / VX 200/4 / AQUALINE



RHO - Protective cover for HX 3000 / HXC 3000 / PERFORM 3000 - 3000 XL / PRESTIGE 3000 / ST 2,36 - 3,60 / TR 2,36 - 3,60 / HP 2,26 / XT 3,78 ; Dimensions : 70 x 45 x 50 cm

Protective cover for HX(C) 3000 / PERFORM 3000 - 3000 XL / PRESTIGE 3000 / ST 2,36 - 3,60 / TR 2,36 - 3,60 / HP 2,26 / XT 3,78 ; Dimensions : 70 x 45 x 50 cm



RPM - Plug kit for all models: 2 x 16A /230V sockets, 1 x CEE17 16A/230V socket, 1 x 32A/230V socket, 1 x 16A/400V socket

Plug kit for all models: 2 x 16A /230V sockets, 1 x CEE17 16A/230V socket, 1 x 32A/230V socket, 1 x 16A/400V socket